



# *SpeedMixer*<sup>TM</sup>

GermanEngineering  
by Hauschild



*DAC 700 FVZ / VAC-P / LR*



Please scan  
for more  
information  
about our  
products.





# SpeedMixer™

GermanEngineering  
by Hauschild

## Technical Data

	700.1 FVZ	700.2 VAC-P	700.1 FVZ LR	700.2 VAC-P LR
Mixing Capacity <sup>1</sup> (g)	Up to 700	Up to 700	Up to 700	Up to 700
Speed (rpm)	800 – 2100	800 – 2100	800 – 1850	800 – 1850
Mixing time (s)	1 – 600	1 – 600	1 – 600	1 – 600
Voltage (V)/ Frequency (Hz)	230 / 50 – 60	230 / 50 – 60	230 / 50 – 60	230 / 50 – 60
Power consumption (kW)	1,2	1,2	1,2	1,2
Height – Lid open (mm)	960	1030	960	1030
Width (mm)	440	440	440	440
Depth (mm)	640	700	640	700
Weight (kg)	72	90	72	90
Vacuum option	no	yes	no	yes
LR Option – high performance	no	no	yes	yes
Additional features	Touch screen Vision panel Variable speed Selectable fixed speed 20 programme storage spaces Key lock (QS) Imbalance sensor RS-232 interface			

<sup>1</sup> incl. material, mixing cup, cup holder. These values are nominal and they might change depending on the physical characteristics of the material.

Subject to modifications – Last update 29/01/2020



Hauschild & Co. KG  
 Waterkamp 1 · 59075 Hamm / Germany  
 Phone +49 (0)2381 48205-0  
 Telefax +49 (0)2381 48205-17  
 E-Mail info@speedmixer.de  
 www.speedmixer.de